



ND 100 GLT Panic Button



- ▶ Panic button in DC circuit technology (GLT)
- ▶ For connecting to an intrusion panel
- ▶ Tamper contact
- ▶ Cable can be surface- or flush-mounted
- ▶ Cap with cover as trigger protection (optional)

The ND 100 GLT panic button is used for unobtrusively and manually triggering alarms at work places that are in potential danger of being held up, such as banks, jewelry shops, businesses, private households etc.

Certifications and Approvals

Region	Certification	
Germany	VdS	G 195065, C ND 100 GLT
Europe	CE	ND 100 GLT

Parts Included

Type	Qty.	Component
ND 100 GLT	1	Panic button incl. adhesive seal

Technical Specifications

Alarm contact (Changeover contact)	30 V _~ /300 mA
Tamper switch (Changeover contact)	30 V _~ /300 mA
Ambient temperature	0 °C to 50 °C
Ambient climates	DIN 40 040 R14
Protection category	IP 40
Environmental class	2
Housing	
• Housing material	ABS
• Housing color	RAL 9002
• Cover color	Gray
Weight	Approx. 0.07 kg
Dimensions (D x H)	81 x 31 mm

Ordering Information

ND 100 GLT Panic Button

For unobtrusively and manually triggering alarms at work places that are in potential danger of being held up

ND 100 GLT

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3453
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by